

Loading Instructions: Power User Plus Pack – The VL Board

1) Load the 6 Custom Board Voices

Find the files **VL TUTOR.W2B** and **VL TUTOR.W3B**

Copy these to your SmartMedia or USB drive.

Press [FILE]

Press [F1] CONFIG

Press [SF1] CURRENT

Select your CARD or USB device

Press [F3] LOAD

Navigate to the "PluginAllBulk" file type that matches the slot number of your PLG150-VL. If, for example, your PLG150-VL is in slot 1, use the "PluginAllBulk1" File type; if your PLG150-VL is in slot 2, use the "PluginAllBulk2" File type; if your PLG150-VL is in slot 3, use the "PluginAllBulk3" File type to load.

This will load the 6 custom locations of Bank 33/02 with six new VL Element Voices.

2) Load the VOICE EDITOR File

Find the files:

VL TUTRS1.W7E and **VL TUTRS1.W8E** for Slot 1

VL TUTRS2.W7E and **VL TUTRS2.W8E** for Slot 2

VL TUTRS3.W7E and **VL TUTRS3.W8E** for Slot 3

Copy the appropriate set to your SmartMedia/USB device or you can Open the file with the Voice Editor program. Load up the file that corresponds with your VL Slot number to a SmartMedia Card/USB device **or** open them with the "VOICE EDITOR FOR MOTIF ES 6/7/8"

From SmartMedia/USB device

Press [FILE]

Press [F1] CONFIG

Press [SF1] CURRENT

Select your CARD or USB device

Press [F3] LOAD

Navigate to the "VOICE EDITOR" file type and load the Voices to your Motif ES. Loading the Voice Editor type file will load the USER1, USER2, USER DRUM, and PLUGIN USER Voices.

If you choose to open the File in the VOICE EDITOR FOR MOTIF ES 6/7/8, The normal USER1 and USER2 banks are present as well as the PLUG-IN USER bank for your slot.

Select Transmit (CTRL + T) and select the appropriate PLUG-IN USER Bank.

Press START to send the bank to the Motif ES.

Troubleshooting Tip: If the very first PLG150-VL Voice: (A01) "SuperJazz" does not sound like Trumpet go back to step #1) and load the Custom VL Board Voices...

Setup Tips: See the "PLG150-VL: A Getting Started Guide" for information on setting up your Breath Controller and background on the VL technology.

In UTILITY mode of the Motif ES you have several parameters that can affect your BC experience:

- Press [UTILITY]
- Press [F1] GENERAL
- Press [SF1] TG

You can set an overall Breath Controller Curve.

- Press [SF4] OTHER
- You can set the "Ctrl Reset" = **HOLD**

By setting Controller Reset to "Hold" – you will not have to reset the Breath Controller for each Voice that is set for BC.

- Press [STORE] to lock in your Utility Mode settings.